



# Battery Cabinet

## 1- Introduction of Product

Different types of Faratel Battery Cabinets are equipped with Sealed lead-Acid (SLA) batteries that are known as maintenance free. These products are usable with different kinds of Faratel UPSs in order to increase back up time.

### 1-1- Advanced Features

- Equipped with Sealed lead-Acid (SLA) batteries (Maintenance free)
- Equipped with internal charger (Optional)
- Reversed battery connection protection using a special connector
- Equipped with special terminal in order to connect several battery cabinets to increase back up time
- Small footprint thanks to ability of lying on another battery cabinet

## 2-Technical Specification Table

Row	Model	Battery type	Number of batteries	Voltage (V)	Charger	Dimensions [W*D*H] (mm)		Net weight (Kg)	Shipping weight (Kg)
1	SBC240-8.5	Sealed-Lead Acid 12V	20	240	No	With Handle: Net dimensions: Shipping dimension:	490*647*135 440*614*132.5 580*730*380	63	72.5
2	SBC240M-CHR-PRZ-BLK	Sealed-Lead Acid 12V	20	240	Yes	Net dimensions: Shipping dimension:	440*760*1000 460*780*1120	55	61
3	SBC48-26	Sealed-Lead Acid 12V	4	48	No	With Handle: Net dimensions: Shipping dimension:	490*533*181 444*500*177 580*680*410	46	56
4	SBC48-40	Sealed-Lead Acid 12V	4	48	No	With Handle: Net dimensions: Shipping dimension:	490*533*181 444*500*177 580*680*410	66	76
5	SBC48-17-P	Sealed-Lead Acid 12V	8	48	No	With Handle: Net dimensions: Shipping dimension:	483*542*90 440*512*88 530*620*205	29.3	31.3
6	SBC96-8.5-P	Sealed-Lead Acid 12V	8	96	No	With Handle: Net dimensions: Shipping dimension:	490*533*181 440*512*88 530*620*205	46	56
7	SBC 96-26-AB	Sealed-Lead Acid 12V	8	96	NO	With Handle: Net dimensions: Shipping dimension:	490*533*181 440*512*88 530*620*205	66	76
8	SBC 96-40-AB	Sealed-Lead Acid 12V	8	96	NO	With Handle: Net dimensions: Shipping dimension:	490*533*181 440*512*88 530*620*205	66	76

## 3-Battery Cabinets and their Compatible UPS

ROW	Battery cabinet model	Compatible UPSs
1	SBC240-8.5	CAD10KX1-RT4U , CAD10KX3-RT4U , SDC6000X-RT-3U
2	SBC240M-CHR-PRZ-BLK	CAD10KX1-RT4U, SDC6000X-RT-3U, CAD10KX3-RT4U,
3	SBC48-26	DSS1500X-RT, DSS2000X-RT, SSP1500B-RT-18, SSP2000X-RT, SSP3000X-RT, SDC1500X-RT, SFR5000DT-SFR3000DT
4	SBC48-40	DSS1500X-RT, DSS2000X-RT, SSP2000X-RT, SSP3000X-RT, SDC1500X-RT, SFR5000DT, SFR3000DT
6	SBC48-17-P	DSS1500X-RT, DSS2000X-RT, SDC1500X-RT, SSP1500B-RT, SSP2000X-RT , SSP3000X-RT
7	SBC96-8.5-P	DSS3000X-RT, SDC2000X-RT, SDC3000X-RT
8	SBC96-26-AB	DSS3000X-RT, SDC2000X-RT, SDC3000X-RT
9	SBC96-40-AB	DSS3000X-RT, SDC2000X-RT, SDC3000X-RT

## 4- How to Contact Faratel

### 4-1- Central Sales Department

Address: Faratel Bldg., No. 21, Kandovan Alley (Opposite of Nejatolahi St.), Engelab St., Tehran, Iran

Postal Code: 1131834914

Telephone: (+98 21) 6670 0001 up to 5  
(+98 21) 61922

Fax: (+98 21) 6670 9493

Email: sales@faratel.com

URL: <http://www.faratel.com>

### 4-2- Central Customer Service

Address: Faratel, Shahid Abdolrahimi St., 17 Shahrivar St., Sanay-e Felezi St., Fifth Kilometer of Old Karaj Rd., Tehran, Iran

Postal Code: 1378763511

Telephone: (+98 21) 6680 9495 up to 7  
(+98 21) 61922

Fax: (+98 21) 6680 5525

Email: support@faratel.com

URL: <http://www.faratel.com/support/>

In order to find the nearest authorized representatives of Customer Service in Iran please refer to the above URL.